

(12)

EUROPEAN PATENT APPLICATION

(43) Date of publication:  
19.07.2000 Bulletin 2000/29

(51) Int. Cl.<sup>7</sup>: H04L 27/26, H04L 27/38

(21) Application number: 99100737.8

(22) Date of filing: 15.01.1999

(84) Designated Contracting States:  
AT BE CH CY DE DK ES FI FR GB GR IE IT LI LU  
MC NL PT SE  
Designated Extension States:  
AL LT LV MK RO SI

(72) Inventor:  
Kraiem, Besma  
c/o Sony International (Europe) GmbH  
70736 Fellbach (DE)

(71) Applicant:  
Sony International (Europe) GmbH  
10785 Berlin (DE)

(74) Representative:  
MÜLLER & HOFFMANN Patentanwälte  
Innere Wiener Strasse 17  
81667 München (DE)

(54) Quasi-differential modulation/demodulation method for multi-amplitude digital modulated signals and OFDM system

(57) The invention proposes the separate processing of the phase and amplitude of multi-amplitude digital modulation techniques, such as a QAM. The phases are differentially modulated and the amplitudes coherently processed. Also proposed is a method to correct the amplitude distortion of the symbols on each subcarrier, either from the QAM signal itself or from any PSK signal, if available. The invention shows that differential modulation/demodulation of multi-amplitude signals

with no equidistant phases such as QAM is possible. Complex equalizer means to perform a channel estimation is no more needed as for coherent systems. Further, no pilot subcarriers are needed, thus the bandwidth efficiency is much higher. Furthermore, the frequency synchronization of differential demodulated signals is less complex. An implementation proposal of the new modulation/demodulation technique is described.




Fig. 1

## Description

**[0001]** The invention relates to a modulation/demodulation method for multi-amplitude digital modulated signals with non-equidistant phases transmitted via an orthogonal frequency division multiplexing (OFDM) communication channel and also refers to an OFDM system for the transmission of information by multi-amplitude digital modulated signals from a transmitter to a receiver via a radio channel.

**[0002]** Orthogonal frequency division multiplexing (OFDM) has gained Increasing interest in wireless communication systems during the last years, in particular for DAB (Digital Audio Broadcast) and DVB-T (Digital Video Broadcast Television). It has been considered for transmitting high data rate over frequency selective radio channels.

**[0003]** The principle of OFDM transmission technique is to devise an available bandwidth Into several subchannels with smaller bandwidths. Thus the symbol length increases and the inter symbol interference (ISI) is combated. On the other hand, each subchannel is considered to be frequency non-selective. The amplitude and phase distortion caused by multipath effects is accordingly described by one factor.

**[0004]** In coherent transmission systems that distortion is removed by channel estimation. For this purpose known symbols are sent on pilot subcarrier(s). On the receiver side the amount of channel distortion is processed from the received known symbols and is used to correct the rest of the data before demodulation.

**[0005]** Channel estimation is not required, if differential modulation is used. The information Is encoded In the ratio of successive symbols on the same subcarrier. Thus, the channel distortion is cancelled at the receiver, since it is assumed to be constant during successive OFDM symbols.

**[0006]** However, differential modulation and demodulation have been only described for low-order single-amplitude modulation schemes, such as PSK (Phase-Shift Keying) and QPSK (Quadrature Phase-Shift Keying). As for a specific example, reference is made to document DE 195 40 250 C1 describing a demodulation scheme based on the assumption that the demodulated complex symbols are associated to respectively transmitted symbols via a rotational symmetric constellation diagram so that approximative estimations for the phase-shift lead to applications with reasonable results.

**[0007]** For multi-amplitude signals such as QAM (Quadrature Amplitude Modulation) only coherent modulation is used, and thus channel estimation is always required (see e.g. EP 0 734 132 A2).

**[0008]** It is an object of the present invention to teach a more simple modulation/ demodulation method and system for multi-amplitude digital modulated signals with non-equidistant phases, in particular QAM signals transmitted via an OFDM communication channel without the necessity of using pilot carriers.

**[0009]** According to the teaching and the characterizing features of claim 1, this problem is solved with the idea that the amplitudes of said digital modulated signals should be separately and coherently processed, whereas for the phases of respectively subsequent symbols on the same subcarrier differential modulation and demodulation is provided.

**[0010]** Advantageous details, improvements and embodiments are the subject of dependent claims.

**[0011]** An orthogonal frequency division multiplexing (OFDM) system for the transmission of information by multi-amplitude digital modulated signals from a transmitter to a receiver via a radio channel in accordance with the invention is the subject-matter of and defined in claim 9. Specific embodiments and advantageous supplements and improvements are defined in further dependent claims.

**[0012]** For a comprehensive explanation of the invention the following description is divided in chapters.

**[0013]** In **Chapter I** the OFDM transmission model used for simulations and the channel models are first described.

**[0014]** In **Chapter II** the simulation of coherent modulated 16 QAM is presented.

**[0015]** In **Chapter III** the principle of the combined coherent/differential (henceforward called quasi-differential) modulation for 16 QAM signals is described as well as the way It was implemented according to a best mode presently known.

**[0016]** In **Chapter IV** the simulation results of both techniques are compared in terms of BER (Bit Error Rate) performance in an AWGN (Additive White Gaussian Noise) channel and in a multipath channel.

**[0017]** Finally as a **Summary** a brief comparison of both systems with respect to implementation complexity will conclude the present description of the invention.

**[0018]** In the following description reference will be made to the accompanying drawings in which

**Fig. 1** is a block diagram of an OFDM system with features according to the invention;

**Fig. 2** is a diagram of the BER performance of coherent 16 QAM signals in an AWGN channel and multipath channel, respectively;

**Fig. 3** is a constellation diagram of 16 QAM symbols before and after phase-differential encoding;

**Fig. 4** depicts a block diagram implementation of a quasi-differential phase encoder (transmitter side);

**Fig. 5** is a block diagram of the implementation of a quasi-differential phase decoder (receiver side);

5 **Fig. 6** shows a data frame structure as used for simulations;

**Fig. 7** is a diagram of the BER performance of quasi-differential 16 QAM signals in AWGN and multipath channels, respectively;

10 **Fig. 8** visualizes a diagram of a BER performance comparison of coherent and quasi-differential 16 QAM in an AWGN channel;

**Fig. 9** is the diagram of a BER performance comparison of coherent and quasi-differential 16 QAM signals in multipath channels; and

15 **Fig. 10** shows constellation diagrams of received QPSK and 16 QAM signals at different stages with an assumed SNR (Signal-to-Noise Ratio) of 35 dB wherein

- **Fig. 10A** visualizes received QPSK signals in a multipath channel;

20 - **Fig. 10B** is a plot of received 16 QAM signals in a multipath channel;

- **Fig. 10C** shows the stage of received QPSK signals after differential phase decoding;

25 - **Fig. 10D** is a Q/I plot of received 16 QAM signals after differential phase decoding;

- **Fig. 10E** depicts a plot of received QPSK signals after passing a hardlimiter on the receiver side; and

- **Fig. 10F** represents a Q/I plot of received 16 QAM signals after amplitude correction.

30

## Chapter I: System Simulations

[0019] In order to evaluate both the coherent transmission scheme and the quasi-differential transmission scheme according to the invention in different environments a baseband simulation tool known under the tradename COSSAP has been used.

35 [0020] The OFDM transmission model used for such simulations is shown in Fig. 1. Briefly, this OFDM system works as follows: The uncoded data stream is first modulated in 16 QAM symbols. Then  $(N - N_{\text{sel}})$  virtual carriers ( $N$  = maximum carriers for FFT;  $N_{\text{sel}}$  = selected carriers) are inserted in the band edges of each OFDM symbol, since they are not used to transmit data. After IFFT (Inversed Fast Fourier Transformation) is processed, a guard interval is inserted at the beginning of each OFDM symbol, containing a copy of its last  $N_G$  samples ( $N_G$  = Samples of guard length).

40

[0021] The blocks of Fig. 1 and their respective function are briefly described in the following:

45

50

55

**Transmitter side (upper part of Fig. 1):**

Reference Number:	Description and Function:
1	Demultiplexer: The adopted frame structure consists of $n$ QPSK symbols followed by $m$ 16 QAM symbols. Thus $(n \cdot 2)$ bits are sent to the QPSK modulator 2, and $(m \cdot 4)$ bits are supplied to a 16 QAM modulator 3.
2	QPSK Modulator: Mapping of 2 bits into QPSK complex symbols.
3	16 QAM Modulator: Mapping of 4 bits into 16 QAM complex symbols.
4	Multiplexer (MUX): Multiplexes QPSK and 16 QAM symbols into a frame, as shown in Fig. 6.
5	Phase-Differential Encoder: The phases of subsequent symbols on the same subcarrier are differentially modulated, whereas the amplitude is kept unchanged (see functional block diagram of Fig. 4).

- 5  
6 Null Symbol Generator: The unused subcarriers at the band edges are set to zero.
- 10  
7 MUX: The data and null symbols are multiplexed into an OFDM symbol, where the subcarriers at the edges are equal to zero.
- 15  
8 IFFT: Inverse FFT is performed on N data samples to produce a baseband OFDM modulated signal.
- 20  
9 Insertion of guard interval: A copy of the last  $N_G$  samples of the time domain OFDM symbol are inserted before each symbol in order to reduce the effect of multipath interference.
- 25  
10 Quadrature Modulator: The input signal is used to modulate carriers having a  $90^\circ$  phase difference.
- 30  
11 Digital-to Analogue converter (D/A-converter).
- 35  
12 Up-Converter: The signal is converted by a frequency converter to a given carrier frequency for transmission.
- 40  
13 Radio Channel: The radio channels used for simulations are described further below in this chapter.

**Receiver side (lower part of Fig. 1):**

- 45  
14 Down-Converter: The received signal is converted from the carrier frequency down to an intermediate frequency.
- 50  
15 Analogue-to-Digital converter (A/D-converter).

- 5                   **16**                   Quadrature Demodulator: The OFDM signal is detected from the intermediate frequency and the baseband signal is generated.
- 10                   **17**                   Time Synchronization: A FFT window is generated indicating the effective symbol portion of the OFDM symbol for removing the guard interval.
- 15                   **18**                   FFT: Fast (discrete) Fourier Transformation is performed on the OFDM symbol to generate the complex frequency-domain symbols.
- 20                   **19**                   Demultiplexer (DEMUX): The input signal is demultiplexed into the useful data to be sent to a phase differential decoder 21 and the unused subcarriers at the band edges are removed in 20.
- 25                   **20**                   Delete unused subcarriers: The null symbols inserted by null symbol generator 6 at the transmitter are removed and deleted.
- 30                   **21**                   Phase Differential Decoder: The phases of subsequent symbols on the same subcarrier are differentially demodulated, whereas the amplitude is coherently processed (see block diagram implementation of Fig. 5).
- 35                   **22**                   DEMUX: According to the frame structure QPSK symbols are sent to a hardlimiter 23 and a running mean amplitude generation means 24 and the following QAM symbols are amplitude-corrected in 25.
- 40                   **23**                   Hardlimiter: The received QPSK symbols are hard-limited before demodulation.
- 45
- 50
- 55

**24** Running mean of amplitude: Since the amplitude of the QPSK symbols is definitely "1", the amount of amplitude distortion each subcarrier is determined from the QPSK signal, and supplied to block 25 for correction of the amplitude of the QAM symbols.

**25** Correction of amplitude: The amplitude of the received QAM symbols is corrected by the factor calculated by block 24.

**26** QPSK Demodulator: Demapping of QPSK complex symbols into corresponding bits.

**27** 16 QAM Demodulator: Demapping of QAM complex symbols into corresponding bits.

**28** MUX: Multiplexing of QPSK and QAM bits according to the adopted frame structure.

**[0022]** Two channel models have been considered for simulation: An additive white Gaussian noise channel (AWGN) and a frequency selective channel model proposed by ETSI (European Telecommunications Standards Institution) for the Universal Mobile Telecommunication System (UMTS). The latter is a Wide Sense Stationary Uncorrelated Scattering (WSSUS) channel model, that assumes that the received signal is represented by the sum of six delayed replicas of the input signal, weighted by independent zero-mean complex Gaussian time variant processes. The relative path loss and delay of each path for typical indoor environment is given in the Table 1 below:

Tap	Relative Delay (nsec)	Average Path Loss (dB)
1	0.0	0.0
2	50	-3.0
3	110	-10.0
4	170	-18.0
5	290	-26.0
6	310	-32.0

**Table 1: Parameter of the multipath channel model used for simulations**

**[0023]** On the receiver side the guard interval is first removed by windowing. The synchronization is not considered here. After the signal has been transformed into the frequency domain by FFT, the virtual carriers are extracted and the QAM demodulation is performed.

**[0024]** For the analysis the following system parameters have been used:

FFT carrier size:  $N = 64$   
 Guard length:  $N_G = 7$  samples  
 Useful time:  $N_{\text{used}} = 64$  samples  
 Symbol time:  $N_{\text{Sym}} = 71$  samples  
 5 Selected carriers:  $N_{\text{sel}} = 56$   
 Sampling frequency:  $B = 30$  MHz

## Chapter II: Coherent Modulation

10 **[0025]** As mentioned above, in the case of coherent modulation pilot symbols should be inserted to help channel estimation in the receiver. Normally, each frame contains a number of pilot symbols on different subcarriers. In the receiver the amount of distortion of the pilot subcarriers is interpolated in the time and frequency domains, in order to estimate the channel response over the frequency band of interest.

15 **[0026]** To simplify simulations it was assumed that one OFDM symbol with all sub-carriers set to a known value ( $I = 1, Q = 0$ ) is sent at the beginning of each frame. On the receiver side that OFDM symbol is first filtered using a complex FIR filter, in order to shorten the effect of additive white Gaussian noise. It is then used as a measure of channel distortion and the following data symbols are correlated by equivalent factors. The simulation results over AWGN and UMTS channels are shown in Fig. 2:

20 Curve "a" shows an ideal demodulation condition for AWGN. Curve "b" visualizes the coherent demodulation of 16 QAM signals over an AWGN channel causing a SNR degradation of about 1dB at a BER of  $10E-3$ . This is due to the fact that the channel estimation factor for every subcarrier is gained from a noisy pilot symbol in spite of FIR filtering. Further SNR degradation of about 2,5 dB is observed, when a multipath channel UMTS is assumed (curve "c").

**[0027]** These results can be improved by averaging the channel estimation factors over several frames, thus the effect of additive white Gaussian noise can be further shortened.

## Chapter III: Quasi-Differential Modulation according to the Invention.

30 **[0028]** The reason why quadrature amplitude modulated (QAM) signals can not be differentially processed as with DQPSK is the multi-amplitude constellation of QAM signals. The result would be endless many amplitude levels after a few symbols have been differentially modulated. This is, however, an undesired property that complicates the implementation.

35 **[0029]** Thus the idea of the invention is the separate handling of amplitude and phase of QAM signals. If only the phase of 16 QAM symbols are differentially modulated while keeping their original amplitudes, there would be endless many phase levels at three amplitudes (see Fig. 3). Of course, this is less bothersome than it is the case with many amplitude levels.

**[0030]** As shown in Fig. 4 and Fig. 5 the phases of subsequent symbols  $\phi_k$  and  $\phi_{k-N}$ , respectively on the same subcarrier are differentially modulated and demodulated, whereas the amplitude  $A_k$  is coherently processed.

40 **[0031]** The phase rotation on every subcarrier is no more relevant. Preferably and in accordance with the invention the amplitude distortion of the QAM signal due to frequency selectivity of the channel is separately corrected. The information about the correcting factor for every subcarrier is preferably taken from the QAM symbols whose phase is unique to them. This is the case for all symbols not located at the diagonals of the Q/I diagram. In particular, this is the case for 8 of the 16 symbols as shown in the constellation diagram of Fig. 10D. Constellation diagrams for QPSK and 16 QAM symbols at different stages with an assumed SNR of 35 dB are depicted in Fig. 10A to 10F with the respective signal characterization indicated in the respective headline.

45 **[0032]** The correcting factors for the amplitude can be easier computed when a combined QPSK/16 QAM system is adopted. Often, wireless broadband systems adopt QPSK modulation of control data, for better robustness in frequency selective channels, and 16 QAM or higher modulation for useful data. In the system used for simulation, the frame structure of Fig. 6 has been adopted comprising 200 OFDM symbols in the QPSK modulated control signal and 4800 OFDM symbols in the 16 QAM modulated data signal, i.e., one frame contains 5000 OFDM symbols.

50 **[0033]** Since QPSK symbols have definitely the amplitude "1", and the channel is supposed to be static during one frame, the amount of amplitude distortion of the QPSK signal can be easily determined and used for correction of the QAM signal.

**[0034]** Furthermore, a running mean of the amplitude correcting factor can be performed during the QPSK transmission, in order to shorten the effect of additive white Gaussian noise.

55 **[0035]** If only 16 QAM signals are available, a running mean of the correcting factors can also be performed over a time window, where the channel is supposed to be static.

**[0036]** Quasi-differential demodulation in an AWGN channel causes a SNR degradation of about 5.5 dB at a BER of  $10E-3$ ; see Fig. 7, curve "f" - compared to curve "d" referring to an ideal AWGN channel. The BER performance over a



multipath channel UMTS is identical with that over an AWGN channel as visualized by curve "e" in Fig. 7. This denotes, that the multipath effect is fully shortened with the quasi-differential demodulation technique according to the invention. The benefit of this new technique is therefore major in frequency-selective radio channels.

#### 5 Chapter IV: Comparison of BER performance

[0037] The BER results of both techniques are depicted in Fig. 8 for AWGN and in Fig. 9 for the multipath channel.

[0038] Fig. 8 teaches that coherent modulation technique with channel estimation performs considerably better than the quasi-differential modulation over the AWGN channel. Curve "h" for the coherent modulation comes close to the ideal curve "g" by approximately 1 dB, whereas curve "j" for the quasi-differential technique shows a smaller decrease of BER as SNR increases.

[0039] However, the excellent performance of the 16 QAM quasi-differential modulation technique according to the invention becomes obvious when considering the multipath channel situation shown in Fig. 9. Curve "k" again shows for comparison the ideal situation for AWGN. The SNR degradation of curve "m" depicting the BER performance for quasi-differential demodulation according to the invention compared to the coherent demodulation of curve "e" is most at a BER of  $10E-3$ , and amounts to only 2 dB. For higher and lower BERs the degradation becomes constantly smaller.

#### Chapter V: Summary

[0040] A novel incoherent demodulation technique for QAM signals has been presented. The BER performance of this technique has been analyzed and compared to the coherent one.

[0041] It can be concluded that the advantage of the coherent demodulation is the SNR gain of maximum 2 dB at a BER of  $10E-3$ . However, this can be further minimized when the additional overhead for channel estimation is used for higher coding of the quasi-differential modulated signal.

[0042] Furthermore, when considering the implementation aspects of both techniques compared here, it should be noticed that the differential technique according to the invention is less complex since the frequency synchronization of differential demodulated signals is easier. In particular, complex equalizers to perform channel estimation are no more needed as for coherent systems. Also, no pilot subcarriers are needed and thus the bandwidth efficiency is much higher.

#### Claims

1. A modulation/demodulation method for multi-amplitude digital modulated signals with non-equidistant phases transmitted via an orthogonal frequency division multiplexing (OFDM) communication system **characterized in that** the amplitude of said signals are separately and coherently processed, whereas the phases of respectively subsequent symbols on a same subcarrier are differentially modulated and demodulated, respectively.
2. The method of claim 1, **characterized in that** said amplitudes are coherently transmitted and are corrected in the receiver.
3. The method of claim 2, **characterized in that** at the demodulation stage the amplitude distortions of said multi-amplitude digital modulated signals due to frequency selectivity of the respective channel are separately corrected on each subcarrier.
4. The method according to at least one of the preceding claims, **characterized in that** said multi-amplitude digital modulated signals are quadrature amplitude modulated (QAM) signals.
5. The method according to claim 4, **characterized in that** the correction factor for every subcarrier is determined from those QAM symbols whose phase is unique to them.
6. The method of claim 4, **characterized in that** the correction factors for the subcarrier amplitudes of said QAM symbols are computed from quadrature phase shift keying (QPSK) signals combined in one respective frame of a plurality of OFDM symbols comprising a defined number of QAM data symbols and a defined number of QPSK control signals.
7. The method according to claim 4, **characterized in that** sixteen QAM symbols are adopted as said QAM signals.

8. The method of claim 7, **characterized in that** for amplitude correction of the receiver, a running mean of the correction factor is performed over a defined time window.
9. The method of claim 4, **characterized in that** a frame structure is adopted comprising nQPSK symbols followed by m 16 QAM symbols.
10. An orthogonal frequency division multiplexing (OFDM) system for transmission of a multi-amplitude digital modulated signal from a transmitter to a receiver via a radio channel **characterized in that**
- on the transmitter side, phase differential encoder means (5) are provided for differentially modulating subsequent symbols on the same subcarrier,
  - on the receiver side, differential phase decoding means (21) are provided for demodulating said respectively subsequent symbols on said same subcarrier, and in that
  - means are provided on said both sides for coherent processing of the amplitudes of said signals.
11. The OFDM system of claim 10, **characterized in that** said transmitter is adapted to process a coded data stream with a block frame structure consisting in each frame of a sequence of n quadrature phase shift keyed (QPSK) control symbols followed by m sixteen quadrature amplitude modulated (16 QAM) data symbols and comprising
- a demultiplexer means (1) for separating said control symbols and said data symbols, and
  - for feeding said control signals to QPSK modulator means (2) for mapping of two bits each into QPSK complex symbols and for supplying said data symbols to a 16 QAM modulator means (3) for mapping of four bits each into 16 QAM complex symbols,
  - first multiplexing means (4) for multiplexing said QPSK complex symbols and said 16 QAM complex symbols and for supplying the resulting data stream to
  - a phase differential encoder means (5) for differential modulation of the phases of respectively subsequent symbols on a same subcarrier and keeping the respective amplitudes of said symbols unchanged,
  - second multiplexing means (7) for transferring the resulting data symbol stream into OFDM signals that are subject to an inverse fast Fourier transformation (8) to produce a baseband OFDM-modulated signal,
  - quadrature modulator means (10) for modulating said baseband signal with carriers having 90° phase difference and supplying the thus modulated signal to
  - D/A-converter means (11) followed by an up-converter means (11) to hook the analog D/A-converter output signal to a given carrier frequency for transmission.
12. The OFDM system of claim 11, **characterized in that** null symbol generating means (6) are provided for setting unused subcarriers leaving said phase differential encoder means (5) at the band edges to zero.
13. The OFDM system of claim 11 or 12, **characterized in that** for reducing multipath interference effects a guard interval inserting means (9) is provided for inserting before each symbol a copy of a defined number of the last samples of the inverse fast Fourier transformed time domain OFDM symbols.
14. The OFDM system of any of the preceding claims 10 to 13, **characterized in that** said receiver is adapted to receive, process and demodulate said radio channel transmitted signal and comprising:
- a down-converter means (14) for converting the received signal from said carrier frequency down to an intermediate frequency;
  - analogue-to-digital converter means for digitizing said intermediate frequency signal;
  - a quadrature demodulator means (16) for detecting and generating a baseband signal from said A/D-converted intermediate frequency;
  - a time synchronizing means (17) for generating a window for fast Fourier transformation indicating the effective symbol portion of the OFDM signal;
  - fast discrete Fourier transformation means (18) for producing complex frequency domain symbols of said effective symbol portion of the OFDM signal;
  - first demultiplexer means (19) for demultiplexing the FFT transformed OFDM signal into useful data and for cancelling unused subcarriers at the band edges;
  - phase differential decoder means (21) for demodulating the phases of subsequent symbols on the same subcarrier with simultaneous coherent processing of the amplitudes;
  - second demultiplexer means (22) for separating QPSK symbols and QAM symbols;

- QPSK demodulator means (26) for demapping of said QPSK complex symbols into corresponding bits;
- QAM demodulator means (27) for demapping of said QAM complex symbols into corresponding bits; and
- third multiplexing means (28) for multiplexing of said demodulated QPSK bits and said demodulated QAM bits according to the adopted frame structure.

5  
15. The OFDM system of claim 14, **characterized in that** the QPSK complex symbols output from said second demultiplexer means (22), on the one hand, are sent via hardlimiter means (23) to said QPSK demodulator means (26) and, on the other hand are sent to an amplitude distortion determining mean for generating a running mean of the respective QPSK signal, and in that the QAM complex symbols output by said second demultiplexer means (22) is  
10 supplied to an amplitude correction means (25) for amplitude correction according to the respective running mean of amplitude before supplying the amplitude corrected QAM complex symbols to said QAM demodulator means (27).

15

20

25

30

35

40

45

50

55




Fig. 1




Fig. 2




Fig. 3




Fig. 6




Fig. 4




Fig. 5




Fig. 7




Fig. 8






Fig. 9

Received QPSK Signal In Multipath Channel




Fig. 10 A

Received 16QAM Signal In Multipath Channel




Fig. 10 B




Fig. 10D




Fig. 10C

Received 16QAM Signal after amplitude correction




Fig. 10F

Received QPSK Signal after Hardlimiter




Fig. 10E



European Patent  
Office

# EUROPEAN SEARCH REPORT

Application Number  
EP 99 10 0737

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int.Cl.6)
X	EP 0 869 649 A (BOSCH GMBH ROBERT) 7 October 1998	1-4, 7, 10	H04L27/26 H04L27/38
Y	* abstract *	6, 8, 9, 11-14 12, 13	
A	* line 46 - line 51 * * column 2, line 13 - line 16 * * column 2, line 35 - line 36 * * column 3, line 12 - line 18 * * column 4, line 10 - line 16 * * figures 1-3 *		
Y	EP 0 734 132 A (TOKYO SHIBAURA ELECTRIC CO) 25 September 1996	6, 9, 11-14 10-15	
A	* abstract * * column 2, line 14 - line 33 * * figure 2 *		
X	MORIYAMA S ET AL: "Digital transmission of high bit rate signals using 16DPSK-OFDM modulation scheme" IEEE TRANSACTIONS ON BROADCASTING, MARCH 1998, IEEE, USA, vol. 44, no. 1, pages 115-122, XP002105431 ISSN 0018-9316	10	TECHNICAL FIELDS SEARCHED (Int.Cl.6) H04L
Y	* abstract *	8	
A	* section II (1) to (2) *  * page 116, left-hand column, last paragraph - right-hand column, paragraph 1 * * page 117, left-hand column, paragraph 1 * * figures 1, 2 *	1-4, 11-15	
The present search report has been drawn up for all claims			
Place of search THE HAGUE		Date of completion of the search 11 June 1999	Examiner Langinieux, F
CATEGORY OF CITED DOCUMENTS X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document			

EPO FORM 1503 03.82 (P04C01)



European Patent  
Office

# EUROPEAN SEARCH REPORT

Application Number  
EP 99 10 0737

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int.Cl.6)
A	US 4 683 578 A (BETTS WILLIAM L ET AL) 28 July 1987 * abstract * * column 1, line 56 - column 2, line 3 * ----	5,8	
A	EP 0 729 250 A (TOKYO SHIBAURA ELECTRIC CO) 28 August 1996 * figure 3 * -----	12,13	
			TECHNICAL FIELDS SEARCHED (Int.Cl.6)
The present search report has been drawn up for all claims			
Place of search <b>THE HAGUE</b>		Date of completion of the search <b>11 June 1999</b>	Examiner <b>Langinieux, F</b>
<b>CATEGORY OF CITED DOCUMENTS</b> X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document		T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons ..... & : member of the same patent family, corresponding document	

EPO FORM 1503 03.82 (P04C01)

**ANNEX TO THE EUROPEAN SEARCH REPORT  
ON EUROPEAN PATENT APPLICATION NO.**

EP 99 10 0737

This annex lists the patent family members relating to the patent documents cited in the above-mentioned European search report. The members are as contained in the European Patent Office EDP file on  
The European Patent Office is in no way liable for these particulars which are merely given for the purpose of information.

11-06-1999

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
EP 0869649 A	07-10-1998	DE 19713631 A	08-10-1998
EP 0734132 A	25-09-1996	JP 8265293 A	11-10-1996
		CA 2171418 A	24-09-1996
		CN 1138256 A	18-12-1996
		US 5771224 A	23-06-1998
US 4683578 A	28-07-1987	NONE	
EP 0729250 A	28-08-1996	JP 8237219 A	13-09-1996
		CA 2170094 A	25-08-1996
		US 5694389 A	02-12-1997